

Mobile Surveillance

Requirement

- a. E-Vista 300/500 series (v2.5.0 and up) support.
- b. E-Vista Mobile View 1.1
- c. Mobile phones support JAVA J2ME MIDP2.0, CLDC1.1 and up
- d. Support GSM / WCDMA GPRS service

APN : (Access Point Name) - To express the business type of GPRS

NOTE: Each mobile system has different GPRS setup for cell phone. For different setup to meet each cell phone, please contact with your GPRS provider to confirm your APN of GPRS

- (1) Use GPRS to connect to wap.e-vista.com.tw to download E-Vista Mobile View 1.0
- (2) Select your storage path of mobile phone to save our E-Vista Mobile Surveillance program
- (3) After installation, run "evmv" program to set login configuration
 - (a) IP : Enter your host IP address (ex:61.222.xxx.xx)
 - (b) USERNAME: Enter username (ex: Admin)
 - (c) PASSWORD : Enter password (ex:1234)
 - (d) CHANNEL : Select your channel number
 - (e) CONNECT PORT : Communication port (ex:17860)
 - (f) SPEED : Display speed (SLOW, NORMAL, HIGH, FAST,3G)
 - (g) Enter "LOGIN"

2. Some available (tested) models for your reference:

2G Mobile Phone

Brand	Model
Motorola	A760, A768i, E680, E398, V220, V600, V635, A1200
	MPx220 (Smartphone)
Sony Ericsson	K500i, K700i, K750i, S700i, W800i, Z520i
BenQ	P50
Samsung	SGH-P858
Nokia	6270, 5550

3G Mobile Phone (Please inquire for your GPRS provider to confirm internet function)

Brand	Model
Motorola	V975, E1000, E1070, RAZR maxx V3
Sony Ericsson	K600i, K800i, W900i, Z800i, Z610i, P990i
Nokia	6280, 6288, 7390